

Programming Embedded Systems 2011 / JB

Exercise 3 / 1.2.2011 / Deadline for submitting report 11.2.2011

Return report electronically on address: <https://xprog28.cs.abo.fi/ro.nsf>. If you do not have an ÅA account, please email report to jerker.bjorkqvist@abo.fi

Assistant: Dag Ågren. Dag will be available Tue/Fri afternoons for assistance. If not in the lab, please find him on 4th floor, room A4059.

Equipment and tools

Equipment used: Modtronix SBC65EC single-board computer + daughter board
PC with Microchip MPLAB IDE / MCC18-compiler (both can be downloaded for free from microchip home page: www.microchip.com)

Task

Using exercise 2 as a starting point, this time the system will be enhanced in the following ways:

- A) Make the board react to key pressures
 - Pressing the key will activate the red led
 - Pressing the key again will deactivate the led
 - Use a state simple machine
- B) Interrupt based scheduling
 - Make a interrupt routine, that activate / deactivate the yellow led with a certain interval
- C) Integrate key pressing with the interrupt routine, i.e. make the key press routine as a task, which implements the state machine as in A)

Registers for I/O:

TRIS – register for controlling I/O-port direction

```
TRISBbits.TRISB6 = 0; // pin 6 on port B is set as output
```

LAT – register: latch for output ports

```
LATBbits.LATB6 = 1; // pin 6 on port B is set high
```

PORT – value on port (for reading input)

```
myval = PORTBbits.RB6;
```

Note that register NAME-ADDRESS mapping is found in the via the “p18cxxx.h”, which dependent on your architecture is mapped to the file representing the actual hardware (depending on precompiler definitions). In this case the file “18f6627.h”, which is found in the MCC18 installation folder h- directory (often “c:\mcc18\h”).

Programmable timers on the Microchip 18F6627. The microcontroller has 4 16/8 bit timers, which are programmable. The TOCON register controls the behavior. The TMR0L and TMR0H are the timer counter values (low and high bytes). The timers can be controlled for interrupts, but here only overflow (TMR0L/H == 0).

In order to enable interrupts at regular intervals, a timer must be programmed.

För att skapa avbrott (interrupts) måste en timer programmeras. I 18F66xx via registren

TMR0L – Low byte for 16-bits timer

TMR0H – High byte for 16 bits timer

TOCON – Timer control (kan sättas till 0b00000001)

TOCONbits.TMR0ON - Timer on/off

INTCONbits.TMR0IE – Enable interrupts on timer 0

INTCONbits.TMR0IF – Set if overflow

The timers has to be reset on each interrupt by rewriting to the registers TMR0L TMR0H, and resetting TMR0IF.

Interrupts:

Define in the main routine so that the interrupt vector is in the right place. In a Microchip 18F6627 PIC with bootloader, the high priority interrupt vector is at position 0x808.

(In a bootloader-enabled PIC, everything is shifted from position 0x0 to 0x800).

```
#pragma interrupt HighISR save=section(".tmpdata")
void HighISR(void) {
    if (INTCONbits.TMR0IF) { // Är det en timer0 overflow?
        ...
    }
}

#pragma code highVector=0x808
void HighVector (void)
{
    _asm goto HighISR _endasm
}
#pragma code /* return to default code section */
```

Document what you have done, and submit the documentation and the code you have produced electronically to the address give above.

General rules for documenting projects:

Each report should include:

- Title
- Name
- Date / timeframe when exercise performed
- Group (if not done individually)
- Assumptions on knowledge of the reader
- Own contribution (if performed in group)
- Description of the task / exercise
- Description of the equipment used
- Description of performed work
- Achieved results