

Programming Embedded Systems 2010 / JB

Exercise 4 / 9.2.2010 / Deadline for submitting report 16.2.2010

Return report electronically on address: <https://xprog28.cs.abo.fi/ro.nsf>. If you do not have an ÅA account, please email report to jerker.bjorkqvist@abo.fi

Assistant: Dag Ågren. Dag will be available Mon-Thu afternoons for assistance. If not in the lab, please find him on 5th floor, room A5035.

Equipment and tools

Equipment used: Modtronix SBC65EC single-board computer + daughter board
PC with Microchip MPLAB IDE / MCC18-compiler (both can be downloaded for free from microchip home page: www.microchip.com)

Task

Using exercise 3 as a starting time, this time the system will be enhanced in the following ways:

- Create 2 tasks
 - 1: Use the A/D converter on the board for sampling the NTC (Negative Temperature Coefficient) resistor on the daughterboard
 - 2: Using the value read from the NTC, make the led (red / or yellow) blink with a frequency correlating to the A/D value read

Registers for A/D on PIC18F6627

ADCON0 – register for controlling A/D conversion

Bit 5-2 : Select A/D channel

Bit 1: Start A/D conversion / is A/D conversion in progress ?

Bit 0: A/D module enabled / disabled

ADCON1 – register for controlling A/D

Bit 5-4 : Voltage reference

Bit 3-0: A/D port configuration bits

ADCON2 – register for controlling A/D

Bit 7 – Result format select

Bit 5-3 – A/D Acquisition time

Bit 2-0 – A/D clock source

General rules for documenting projects:

Each report should include:

- Title
- Name
- Date / timeframe when exercise performed
- Group (if not done individually)
- Assumptions on knowledge of the reader
- Own contribution (if performed in group)
- Description of the task / exercise
- Description of the equipment used
- Description of performed work
- Achieved results